



Volts	NO.	C33,C34	C9,C10	R52	R45,R46	R55,R56	R54	R49	ZD4	ZD3	ZD5	EC6	R44	R65	C35	D15,D16
5V	472/500V	330u/10V	1K	6R8/1W	51R/2W	680R	1K5	JUMP	5.7V	JUMP	22u/50V	4R7/0.5W	1K5	2200u/10V		
7.5V	472/500V	220u/16V	750R	10R/1W	100R/2W	1K	2K2	JUMP	8.3V	JUMP	22u/50V	2R2/0.5W	1K8	2200u/16V		
12V	222/500V	100u/25V	1K5	10R/1W	270R/2W	2K2	6K8	JUMP	12.9V	JUMP	22u/50V	3R3/0.5W	1K8	1000u/25V		
15V	222/500V	100u/25V	1K5	15R/1W	330R/2W	2K7	10K	JUMP	16V	JUMP	22u/50V	1R8/0.5W	1K8	1000u/35V	D92-02	
24V	471/1KV	100u/35V	1K5	22R/1W	680R/2W	4K7	15K	12V/1W	15V/1W	12.9V	47u/25V	1R2/0.5W	1K8	1000u/63V	D92-02	
48V	221/1KV	220u/63V	1K5	39R/1W	3K3/2W	10K	36K	33V/1W	33V/1W	27V/1W	47u/25V	2R2/0.5W	1K8	220u/63V	D92-02	
27V	221/1KV	470u/50V	2K	27R/1W	1K2/2W	3K6	27K	18V/1W	18V/1W	18V/1W	47u/25V	1R2/0.5W	1K8	470u/50V	D92-02	
13.5V	222/500V	100u/25V	1K8	10R/1W	270/2W	1K2	10K	JUMP	16.1V	JUMP	22u/50V	1R2/0.5W	1K8	1000u/25V		

Title		
Size	Number	Revision
Date:	23-Jan-2007	Sheet of
File:	C:\Documents and Settings\Administrator\桌面\1390W系列.Ddb	