

# UHP-200W光束灯点灯板



带温控 UHP--100-280W/85--260V 点灯板  
With thermostat UHP-100-280W/85-260V Lampdriver

UHP 光束灯亮度是卤素灯的 3 倍。用 200W-UHP 灯取代 575W 卤素灯亮度高出一倍。UHP 灯寿命最长 3000 小时。

## I 带温控 UHP-100-280W/85-260V 点灯板主要突出特点:

- 1、直接接入 110v 或 220v 交流电压(适应电压 85-260v/AC)。功率因数 0.99(PF: 0.99)。
- 2、5V/DC 控制开机和关机(5V 与主机隔离)，5V 控制灯功率减半。
- 3、灯功率大小用户可以根据需要进行调整。功率减半多少瓦也可调整。
- 4、带有温度控制功能,当风机出现故障时点灯板温升至 80-90 度时会自动开闭,温度降至正常后会自动恢复开机。
- 5、适用于 85-120V 管压,启动电压 3-5KV 的 UHP 灯泡配套。
- 6、启动触发时间 3-5 秒(可根据用户要求设置),二次启动 3-5 分钟(可根据用户要求设置)。
- 7、带温控 UHP-100-280W/85-260V

## I 点灯板有二种输出方式:

- A)、(配套 LCD 投影机)直接输出高压适用于灯泡离点灯板较近的设备配套。
- B)、(配套光束灯)高压包外置式,能将点灯板和灯泡分开较远距离,通常在 1-5 米之间。适用于光束灯、摇头灯、探照灯、UHP 灯老化台、医疗设备配套。

## Lighting board salient features:

- 1、 direct access to 110v or 220v AC voltage (adaptation to voltage 85-260v/AC). The power factor of 0.99 (PF: 0.99).
- 2、 5 V / DC control startup and shutdown (5V host isolation) 5V control lamp power halved.
- 3、 the lamp power size of the user can be adjusted as needed. Power is reduced by half the number of watts is also adjustable.
- 4、 with temperature control, lighting plate temperature rose to 80-90 degrees when the fan fails automatically opening and closing, the temperature dropped to normal after recovery boot.
- 5, suitable for 85-120V tube pressure, supporting start voltage 3-5KV UHP lamp.
- 6, the start trigger time 3-5 seconds (based on user requirements), secondary Kai 3-5 minutes (can be set according to user requirements).
- 7, the thermostat UHP-100-230W/85-260V lighting board two kinds of output ways:
  - a direct output of the high voltage applied to the lamp from a point closer equipment for, such as LCD projectors.
  - b, ignition coil external, can separate lighting board and lights than distance, usually between 1-10 meters. Applied to the beam lamps, searchlights, UHP lamp aging units, medical equipment supporting.



- 1: 220V 输入口特征: 插座为 3 位 2 针, 右边有一个 3 针小插座 (控制口)。
  - 2: 输出口特征: 插座为 4 位 3 针, 左边有 2 个兰色微调电阻。
  - 3: 5v 控制口可以根据用户需求设制, 如不使用控制口输入 220v 电源即能亮灯。
  - 4: 灯功率已设定在 150w, 可以上调至 170w。 200w, 可调到 230w。
- qq: 1599186460  
qq: 1346024717
- 疑定之处请来电询问: 先打 0755-26079669 后打: 18926548327

